

STATION SETS
LOCAL BATTERY
SELECTION FOR GENERAL USE

1.00 INTRODUCTION

This section covers the selection of local battery talking, common battery signaling, dial and manual station sets for general use. It also includes information on message rate service and selection of colored sets.

- Choice of network for these sets is included in the section entitled Transmission Zoning.
- Ringer limitations are included in the section entitled Ringing Bridge Limitations.
- F4 or F5 handsets should be used with local battery sets.

2.00 GENERAL

2.01 Information is contained in tabular form and includes the following:

- Selection by class of service as furnished by Western Electric Company.
- Indication of sets which require modification.
- Indication of sets to be used under particular station conditions.

2.02 Local battery sets are normally used in Zone L and the 6-type dial should be used in this zone.

3.00 MESSAGE RATE SERVICE

Local battery sets may be used for individual and 2-party line manual message rate service, but they cannot be used for tip-party identification on dial service.

4.00 SELECTION OF COLORED SETS

Selection information concerning colored sets is contained in Table A.

TABLE A
SELECTION OF LOCAL BATTERY COLORED SETS

Color	Full	Two-tone	307A 307C	357A 357C
Ivory	-50	-50A	•	
Green	-51	-51A	•	
Gray	-52	-52A	•	
Red	-53	-53A	•	
Brown	-54	-54A	•	
Beige	-55	-55A	•	
Yellow	-56	-56A	•	
Blue	-57	-57A	•	
Ivory	- 4			•

TABLE B

SELECTION OF DIAL OR MANUAL LOCAL BATTERY SETS FOR GENERAL USE IN ZONE 1

Class of Service			Flat Rate			
Type of Service		Individual or Bridged	Ring Party		Tip Party (See 3.00)	
Party Positions			1, 3, 5, 7, or 9	1, 3, 5, or 7 (+) and (-)	2, 4, 6, 8, or 10	2, 4, 6, or 8 (+) and (-)
Type of Ringing	Full Selective	1 party	2 party	4 party	2 party	4 party
	Semiselective		4 party	8 party	4 party	8 party
	Code Div Code		multi-party		multi-party	
Combined Desk Type						
	Dial	Manual				
307	C	A	•	•	•	
307	G*	E*	•	•	•	
309	C	A		•		•
Combined Wall Type				•	•	
357	C	A				
Two-piece Sets						
Hand Tel Set		Subset				
	Dial	Manual				
201 C	A					
202 F	H					
206 C	A*	{ 634BB * 634Y ‡ 634YD ‡ 634YT ‡ 634YDT ‡	•	•	•	
207 C	A*		•	•	•	
211 G	E‡		•	•	•	
212 L	L†				•	•
213 B	E§				•	•
215 C	A§					

*Used when transmitter battery for more than one station is provided from a common source. See BSP on power supply filter for this condition.

†Requires modification when used as a manual station.

‡Requires modification only when used at stations having a common source of battery supply.

§Used when two or more hand telephone sets are connected to a common subscriber set.

•Sets as furnished by Western Electric Company for this service.