

STATION DIALS
TOUCH-TONE® TYPE
SELECTION

1. GENERAL

intended use. Detailed information may be found in the referenced identification section.

1.01 Tables A (Dials) and B (Card Dialers) list the various TOUCH-TONE® dials and their

1.02 This section is reissued to revise Tables A and B.

NOTICE

This document is either
AT&T - Proprietary, or WESTERN
ELECTRIC - Proprietary

Pursuant to Judge Greene's Order of August 5, 1983, beginning on January 1, 1984, AT&T will cease to use "Bell" and the Bell symbol, with the exceptions as set forth in that Order. Pursuant thereto, any reference to "BELL" and/or the BELL symbol in this document is hereby deleted and "expunged".

♦ TABLE A ♦

DIALS

| DIAL | INTENDED USE | REMARKS | SECTION REFERENCE |
|------------------------|---|--|-------------------|
| 22C3 | Master and maintenance control centers of No. 1 and No. 101 ESS | Dial is keyed remotely by automatic test frame to provide frequencies for testing. Also used for normal dialing. | 501-164-102 |
| 22D3 | 2626A1 telephone set, 904E data test center, 10C telegraph test board, attendant circuit for M35 teletypewriter, master control center 4-wire ESS | Similar to 22C3 except for minor variations in the common switch. May be used with 3-type or 4A speakerphone systems. | |
| 22E3 | SCAN, 1616-type CALL DIRECTOR® sets | Has leads for polarity guard, surge protector, amplified handsets and 2/4 wire telephone sets. May be used with 3-type or 4A speakerphone systems. | |
| 35A3A | General purpose 2500 series telephone sets | Has leads for polarity guard, surge protector, amplified handsets, and 2- and 4-wire telephone sets. | 501-164-115 |
| 35D3A | Forms part of 36E dial and 1036E dial | Has leads for polarity guard, surge protector, amplified handsets, and 2- and 4-wire telephone sets. May be used with 3-type or 4A speakerphone systems. | |
| 35F3A | 1B- and 2B-type telephone consoles | | |
| 35H3A | PBX | 50-type dial mounting required | |
| 35J3A | Forms part of 36-type dial for PBX | | |
| 35L3A | Forms part of 36H dial | Similar to 35D3A. May be used with 3-type or 4A speakerphone systems. | |
| 35N3A | 33- and 35-type teletypewriter | Same as 35N1A except marked for "number-letter" dialing | |
| 35P3A | Forms part of 36K dial in DATAPHONE® service provided by 33- and 35-type teletypewriter | Same as 35P1A except marked for "number-letter" dialing. | |
| 35R3A | 2644A telephone set | May be used with 3-type or 4A speakerphone systems. | 501-164-115 |
| 35S3D† (MD) | 2671B1M telephone set | Same as 35C3A except has an additional make contact. May be used with 3-type or 4A speakerphone systems. | |
| 35T3A (A&M Only) | 1A2, 2A2, 1C2, and 2C2 coin telephone sets | Same as 35G3A dial except has an additional set of off-normal contacts. | |
| 35Y3A | General purpose 2500 series telephone sets | | |
| 35Y3D† | 2500-, 2554-, 2555-, and 2558-type telephone sets | | |
| 35AC3A | 2505B telephone set | May be used with 3-type or 4A speakerphone systems. | |
| 35AD4A | 2712-type telephone set, 2900 series DESIGN LINE* telephone sets | Same as 35E4A. | |

♦TABLE A (Contd)♦

DIALS

| DIAL | INTENDED USE | REMARKS | SECTION REFERENCE |
|---------|---|---|----------------------------|
| 35AE3A | 45A9B and 45A9C telephone consoles | Same as 35C3A. May be used with 3-type or 4A speakerphone systems. | 501-164-115 |
| 35AF3A | 2565GK, HK, LK, 2568HU, HAA, and 2580A telephone sets. 1035AF3A dials. | Same as 35C3A. May be used with 3-type or 4A speakerphone systems. | |
| 35AF3D† | 2580- and 2581-type and 2568HAA telephone sets | Same as 35AF3A. May be used with 3-type or 4A speakerphone systems. | |
| 35AG3A | 2872AM telephone set | | |
| 35AT3A | 2960A01M telephone set | Same as 35AG3A except for white buttons and color plate. | 503-301-101 |
| 35AU3A | 2983A01 telephone set | RC type circuit, may be used with 4A speakerphone | 518-450-105 |
| 35AY3A | 2981A01 telephone set | RC type circuit, white buttons and cover plate | |
| | 2991-type telephone set | RC type circuit, white buttons and cover plate | 503-100-129 503-100-130 |
| 70A | 1C- and 2C-type coin telephone sets. 2755A apartment door answering telephone set | Similar to 35T3A. | 501-165-115 |
| 82A2A | 2220B hand telephone set | | 501-165-180 |
| 83A2B | 2220C TRIMLINE® telephone set | Has LED illumination | |

* Trademark of AT&TCo.

† Dial codes in which the last letter has been changed from A to D are recommended replacements for the codes ending in A. The D coded dials have transformers reinforced with steel clips and require approximately 0.070 inch additional mounting space. This space may not be available in some telephone sets.

◆TABLE B◆

CARD DIALERS

| DIAL | INTENDED USE | REMARKS | SECTION REFERENCE |
|-------|---|--|-------------------|
| 36E | 1036E dial, 2660-, 2662-, 2663-, and 2664-type telephone sets | Combination of 35D3A dial and card reading mechanism. Manual dialing when card is in stop position, can be used with speakerphone and polarity guard. | 501-164-116 |
| 36H | 804P3 data auxiliary set | Combination of 35L3A dial and card reading mechanism. Manual dialing when card is in stop position. Dial and card reader are not mechanically connected. A MB5 relay functions as a common switch during card dialing. | |
| 36J | 33- and 35-type teletypewriter | Combination of 35P1A dial and card reading mechanism. Similar to 26C but has two additional special service buttons. | |
| 36K | | Combination of 35P3A dial and card reading mechanism. Same as 36J except marked for "number-letter" dialing. | |
| 36L | 557A and 557B PBX | Combination of 35J3A dial and card reading mechanism. Similar to 26G but has two additional buttons. | 501-164-116 |
| 1036E | For use with rotary dial telephone sets to provide end-to-end signaling when CO is not equipped to handle TOUCH-TONE® calls | Provided with a 36E dial and polarity guard, permits operation of telephone set and adjunct with 3-type or 4A speakerphone system | 501-164-131 |