



TABLE C
CONNECTIONS OF SL-R CAPACITOR LEAD

Set	Number of Lines Picked Up	Use of Buzzer or Ringer	SL-R Lead Connected to Term. Blk Pchg
Mfd Before 4-1-41	1	Common Sig or Line Ringer	L1
	2	Common Sig	L1
Mfd After 4-1-41	1	Common Sig or Line Ringer	1
	2	Common Sig	1

Note 1: A 7-type buzzer on a 36A bracket may be substituted for the ringer as a common or private line audible signal operated from a local power. Install buzzer with cover removed.

Note 2: On 2-line pickup features, the connections shown provide for ringing on line 1. If ringing on line 2 is required, connected ringer lead and yellow capacitor lead to terminals 3 and 4, respectively.

Note 3: To silence ringer permanently, terminate both red and black leads on K terminal.

Note 4: Refer to Fig. 1 for apparatus blank and filter connections.

TABLE D

410A, B, AND C, AND 5410A, B, AND C LINE AND RINGER CONNECTIONS

SET	FEATURES	Connections to Terminals Inside Set										External Connections for Mounting Cord											
		Mounting Cord										Ringer Leads		Capacitor Leads		Line 1		Line 2		To Cutoff Ext Sta, Ringer, or Aux Rec		Signaling Ckt	
410A and 5410A	One-line Pickup, Signaling, and Ringer Cutoff (Ringer in Set)	R	GN	Y	BK	BL	W	R-R	GN-GN	R	BK	Y	SL	Ring	Tip	Ring	Tip	Ring	Tip	S	GND	R	B
		L1	L2Y	S	GND					3	K	4	K	R	GN					Y	BK		
		L1	L2Y	3	4					1	K	2	K	R	GN			Y	BK				
		L1	L2Y	3	4					L1*	K	L2Y*	K	R	GN			Y	BK				
410B and 5410B	One-line Pickup, Signaling, and Extension Cutoff with Ringer Transfer	L1	L2Y	3	4	S	GND			1	K	2	K	R	GN			Y	BK	BL	W		
		L1	L2Y	3	4	S	GND			L1*	K	L2Y*	K	R	GN			Y	BK	BL	W		
		L1	L2Y	3	4	S	GND			1	K	2	K	R	GN			Y	BK	BL	W		
		L1	L2Y	3	4	S	GND			1	K	2	K	R	GN			Y	BK	BL	W		
410C and 5410C	2-line Pickup and Signaling	1	2	3	4	S	GND			1	K	2	K	R	GN			Y	BK	BL	W		
		1	2	3	4	A	K			A	K	L2Y*	L2Y	R	GN	Y	BK					BL	W
		1	2	3	4	S	GND			A	K	L2Y*	L2Y	R	GN	Y	BK						
		1	2	3	4	S	GND			A	K	L2Y*	L2Y	R	GN	Y	BK						
410C and 5410C	2-line Pickup, Signaling, and Common Ringer	1	2	3	4	S	GND	A	K	A	K	L2Y*	L2Y	R	GN	Y	BK			BL	W	R-R	GN-GN
		1	2	3	4	S	GND	A	K	A	K	L2Y*	L2Y	R	GN	Y	BK						
		1	2	3	4	S	GND	A	K	A	K	L2Y*	L2Y	R	GN	Y	BK						
		1	2	3	4	S	GND	A	K	A	K	L2Y*	L2Y	R	GN	Y	BK						

* Indicates terminals on induction coil. Other terminals in table are on terminal strip in set.

FIG. 3—410A, B, AND C, AND 5410A, B, AND C TELEPHONE SETS
(2-line Pickup, Common Ringer, and Signaling)