

TABLE C

**558C AND D LINE AND RINGER CONNECTIONS
(INSIDE WIRE CONNECTIONS)**

FEATURES (SIGNALING INCLUDED WITH ALL FEATURES)									CONNECTIONS TO INSIDE WIRE IN SET													
NUMBER OF LINES PICKED UP	RINGER IN SET USED AS		TURN KEY USED TO CUT OFF				EXCLUSION KEY USED TO CUT OFF		LINE 1		LINE 2		SIGNAL CIRCUIT		EXCLUSION CIRCUIT		CUTOFF CIRCUIT		COM OR PVT LINE RINGER CIRCUIT		KEY EQUIP. OR STA BUSY LAMP CKT (NOTES 3, 4, AND 5)	
	LINE RINGER	COM OR PVT LINE RINGER	EXT STA OR EXT LINE RINGER	EXTERNAL COM OR PVT LINE RINGER	RINGER IN SET	AUXILIARY RECEIVER	EXT STA OR EXT LINE RINGER	RINGER IN SET														
									RING	TIP	RING	TIP	S	GRD	RING	TIP	RING OR R	TIP OR B	R	B	A or BL	A1 or GRD
1	•		•				•		L2	L1			8	7	5	6	3	4			9	12
1	•				•		•		L2	L1			8	7	5	6					9	12
1	•		•		•		•		L2	L1			8	7	5	6	3	4			9	12
1		•	•				•		L2	L1			8	7	5	6	3	4	E1	E2	9	12
1		•			•		•		L2	L1			8	7	5	6			E1	E2	9	12
1		•		•	•		•		L2	L1			8	7	5	6	3	4	E1	E2	9	12
1	•					•	•		L2	L1			8	7	5	6	3	4			9	12
2	•						•		1	2	3	4	8	7	5	6					9	12
2		•					•		1	2	3	4	8	7	5	6			E1	E2	9	12
2		•						•	1	2	3	4	8	7					E1	E2	9	12