



NOTES:

1. INSIDE WIRE CONDUCTOR SHALL BE CONNECTED TO THE GROUND TERMINAL AT THE PROTECTOR OR EQUIVALENT ONLY IF REQUIRED FOR THE SERVICE BEING INSTALLED.
2. DISCONNECT (S) LEAD FROM TERMINAL B WHEN H5AA HANDSET CORD IS USED AND TIP PARTY IDENTIFYING GROUND IS NOT PROVIDED, INSULATE AND STORE.
3. LAMP AND RESISTOR ARE PART OF H5AD HANDSET CORD REQUIRED FOR MESSAGE WAITING FEATURE. IF 220AM OR 2220 BM HAND TELEPHONE SET IS PROVIDED, THE 227-TYPE ADAPTER MUST BE REMOVED.
4. SET WIRED FOR INDIVIDUAL OR BRIDGED SERVICE

5. CHANGE TO 53A LAMP IF COMBINED LENGTH OF HAND TELEPHONE SET CORD AND (ADI BASE) MOUNTING CORD EXCEEDS 15 FEET.
6. REFER TO READ IN 1.01 AND TABLE A FOR ADDITIONAL INFORMATION OR WIRING ARRANGEMENT AND LEAD COLORS OF ADI BASES MANUFACTURED PRIOR TO 10-1-72. (See BSP 502-322-400)
7. H4DB OR H4DU CORD SHALL BE USED FOR INDIVIDUAL OR BRIDGED RINGING, RING PARTY AND TIP PARTY WITHOUT IDENT. GRD.
8. WHEN H4DU CORD IS PROVIDED A 227D AND 231B ADAPTER IS REQUIRED.
9. 220AM, 2220BM, AND 2220BMG ARE EQUIPPED FOR H4DU HANDSET CORD.

\* INSULATED AND STORED

**AD1 (MD) Telephone Base, Connections With 220A (MD), 220AM, 2220B (MD), 2220BM, or 2220BMG Hand Telephone Set**