

COIN STATION SETS

LOCAL BATTERY — SELECTION

1.00 INTRODUCTION

This section covers, in table form, the selection of various types of coin collectors and associated subscriber sets for use on local battery lines employing initial 10-cent operation. Both prepay and postpay types are included.

2.00 GENERAL

2.01 The following tables are included in this section.

Table A—Selection of Dial Prepay Local Battery Coin Collector Sets

Table B—Selection of Manual Prepay Local Battery Coin Collector Sets

Table C—Selection of Dial Postpay Local Battery Coin Collector Sets

Table D—Selection of Manual Postpay Local Battery Coin Collector Sets

2.02 The general information in the tables contains the:

- Types of dials to be used with these sets.
- Types of handsets or transmitters and receivers which are recommended, as well as the types which may be substituted.

- Types of subscriber sets which may be used with each coin collector.
- Types of coin collectors which require rewiring to be used for local battery service.

2.03 When washer rejector and pull bucket return chute features are required, 197-type coin collectors may be arranged in the field for local battery talking per the circuit diagrams in the section entitled Coin Collectors, Prepay, 191CL, DL, GL, and HL, Local Battery Connections.

2.04 When the washer rejector feature of the 198-type coin collector is required, it may be arranged for local battery talking per the circuit diagram in the section entitled Coin Collectors, Postpay, 193GL and HL, Community Dial Office Service, Local Battery Connections.

2.05 Coin collectors are not selected by class of service, as it is assumed that they will be used on individual lines as recommended.

2.06 The selection of coin collector equipment is governed by requirements contained in the section entitled Transmission Zoning. The same color designations have been used in the table to designate **recommended** or **reasonable substitute** equipment.

TABLE A—SELECTION OF DIAL PREPAY LOCAL BATTERY COIN COLLECTOR SETS

Transmission Zone L						Coin Collectors			Subscriber Sets 634YD or 634YE*	* Equipped with S-36 relay for use where long loop or ground potential interferes with normal coin relay operation. ● Recommended Equipment ● Reasonable Substitutes ● Type subscriber set required.
6-Type Dial Only						Trans — Rec Type	Coins			
Handset				Trans	Rec		U. S.	U. S. and Canada		
F1	F2	F4	F5	635	706A					
				●	●	155	GL	HL	●	
				●	●	166	GL	HL	●	
						Handset Type				
	●		●			174	GL	HL	●	
	●		●			176	GL	HL	●	
●		●				191	GL	HL	●	

TABLE B—SELECTION OF MANUAL PREPAY LOCAL BATTERY COIN COLLECTOR SETS

Transmission Zone L						Coin Collectors			Subscriber Sets 634YD or 634YE*	* Equipped with S-36 relay for use where long loop or ground potential interferes with normal coin relay operation. ● Recommended Equipment ● Reasonable Substitutes ● Type subscriber set required.
Handset				Trans	Rec	Trans — Rec Type	Coins			
F1	F2	F4	F5	635	706A		U. S.	U. S. and Canada		
				●	●					
				●	●	155	CL	DL	●	
				●	●	166	CL	DL	●	
						Handset Type				
	●		●			174	CL	DL	●	
	●		●			176	CL	DL	●	
●		●				191	CL	DL	●	

TABLE C—SELECTION OF DIAL POSTPAY LOCAL BATTERY COIN COLLECTOR SETS

Transmission Zone L						Coin Collectors			Subscriber Set 634YD	<ul style="list-style-type: none">● Recommended Equipment● Reasonable Substitutes● Type subscriber set required.
6-Type Dial Only						Trans — Rec Type	Coins			
Handset				Trans	Rec		U. S.	U. S. and Canada		
F1	F2	F4	F5	635	706A					
				●	●	158	GL	HL	●	
				●	●	168	GL	HL	●	
						Handset Type				
	●		●			177	GL	HL	●	
	●		●			178	GL	HL	●	
●		●				193	GL	HL	●	

TABLE D—SELECTION OF MANUAL POSTPAY LOCAL BATTERY COIN COLLECTOR SETS

Transmission Zone L						Coin Collectors			Subscriber Set 634YD	<ul style="list-style-type: none">• Recommended Equipment• Reasonable Substitutes• Type subscriber set required.
Handset				Trans	Rec	Trans — Rec Type	Coins			
F1	F2	F4	F5	635	706A		U. S.	U. S. and Canada		
				•	•	150	K	L		
				•	•	162	A, C	B, D	•	
						Handset Type				
	•		•			152	C	D	•	
	•		•			164	C	D	•	
•		•				182	C	D	•	
Note: All coin collectors listed in Table D require rewiring for local battery service. See section covering local battery connections:										