



| | | |
|--|---|----------------------|
| NZ.P.O. DRAWN CHECKED WIRING CIRCUIT | AMENDMENT PARTICULARS ISSUE DATE APPR. REF. TR. 1039-1732 MOD. | SIZE: M GBW 14430 |
|--|---|----------------------|

AUTO TO AUTO RELAY SET
 O/G TO DEPENDENT UAX NZ 13
 NON-TERMINAL TRAFFIC
 VIA JUNCTION RELAY SET
 VARIABLE FEE 16 UNITS
 WITH REPEAT METERING
 M.A.X.

- NOTES:-**
- FUSING 1.5A. PER RELAY SET.
 - STRAP ——— WHEN NO MULTI-FEE R.S. IS EQUIPPED & CONNECT U20 TO APPROPRIATE METER PULSE FOR FIXED FEE.
 - Ø FOR WIRING SEE GBW 10640 OR EQUIVALENT.
 - JACK POINTS U9 & U11 TO MAKE CONTACT WHEN THE RELAY SET IS REMOVED.
 - ALL WIRING TO BE 25 SWG UNLESS OTHERWISE SPECIFIED.
 - CUT STRAP ——— X ——— WHEN THE JUNCTION RESISTANCE IS LESS THAN 200Ω.
 - THE COILS OF RELAY 'TO' ARE CONNECTED DIFFERENTIALLY.
 - STRAP ——— I ——— WHEN REPEAT METERING CCT IS NOT EQUIPPED.
 - STRAP ——— 0 ——— FOR SINGLE OR FIXED MULTI-FEE METERING WITH TIMED REPETITION.
 - WHEN THIS CCT IS USED IN CONJUNCTION WITH GBW 14470 INSTEAD OF 13500 THE COLOURS OF LEADS M, EF & C ARE TO BE R-B-O, R-B-S & R-B-BN RESPECTIVELY.
- BATT. W. U12-TCE-CBE-TCA6-DDe-AAe-BAe-R4b-RB1b
 R7b-R5b-R6b
 ETH. R. U11-TRI/9-TRI/E-TC24-TC1-J6a-C6a-C54-DAa-DD23
 BB21-DBa-BB1-B21-AA22-AA3-DA21-BA25-A2
 R8a-RB1a-TJ1
 BATT. 22 SWG BK (4B) FUSE-U12
 ETH. 22 SWG R. (4A) ETH BAR-U11
 POS. BATT. R.B-U4-R1b

TO MULTI-FEE RELAY SET.
 GBW 13500 OR EQUIV. WHEN REQUIRED. (NOTE 10)

TO MULTI-FEE R.S.
 GBW 13500 OR EQUIV.
 WHEN REQUIRED

TO DEPENDENT UAX
 VIA OUTGOING
 JUNC. RELAY SET
 & JUNC. (GBW
 13620 OR EQUIV)

TJ 14