



FOR SEQUENCE OF MULTIPLES & WIRING OF OUTLETS SEE EXT LINE CCT GBW 13210 OR EQUIV

FOR WIRING OF OUTLETS SEE MARKER CCT GBW 13230 OR EQUIV

FOR SEQUENCE OF MULTIPLES & WIRING OF OUTLETS SEE EXT LINE CCT GBW 13210 OR EQUIV

FOR SEQUENCE OF MULTIPLES & WIRING OF OUTLETS SEE EXT LINE CCT GBW 13210 OR EQUIV

FOR WIRING OF THESE LEADS SEE PULSE CCT GBW 14710 OR EQUIV

FOR WIRING OF THESE LEADS SEE PULSE CCT GBW 14710 OR EQUIV

FOR WIRING OF THESE LEADS SEE PULSE CCT GBW 14710 OR EQUIV

FOR WIRING OF THESE LEADS SEE PULSE CCT GBW 14710 OR EQUIV

FIG 1B
LINE FINDER

FROM EB TAG ON BANK MULT STRIP CONN GBW 13210 OR EQUIV (BY EXCH LINE CCT ONLY) OR FROM U15 OF PRECEDING EXCH LINE CCT

NZ NOTE A

BUSY CHAIN

OUT

NOTE 2

TO U15 OF NEXT EXCHANGE LINE CCT (ODD CCTS R G) (EVEN CCTS R O) U15 OF LAST CCT TO BE STRAPPED TO UH

- NOTES**
- FUSE 15A PER CIRCUIT
 - SHELF JACK POINTS U15 U17 U19 U75 U77 U78 U79 U81 & U80 USE MAKE CONTACT WHEN RELAY SET IS REMOVED
 - RELAY DR IS DIFFERENTIALLY CONNECTED & IS OPERATED BY AN EARTH APPLIED TO THE 'A' LEAD FROM THE SUBSET ENQUIRY PUSH BUTTON
 - EARTH ON 'A' LEAD OF MAIN EXCH LINE CCT TO BE PERMANENTLY DISCONNECTED
 - 25 POINT UNISELECTORS ON 5+20 EQUIPMENTS
50 POINT UNISELECTORS ON 7+35 & 10+49 EQUIPMENTS
 - FOR ROUTINGS SEE GBW 13280 OR GBW 13300 OR EQUIV
 - ALL WIRING TO BE 0.5mm
 - CONNECTION U76 TO U6 OF ENQUIRY CIRCUIT WIRED ONLY ON 1ST EXCH LINE U76 OF SUBSEQUENT CIRCUITS WIRED TO U76 OF PRECEDING CCT U76 OF EVEN CCTS WIRED IN R 5, ODD CCTS IN R 6
 - STRAP U POINTS 56 58 WHEN FLASHING OF MAIN EXCHANGE OPERATOR BY LOCAL EXTENSIONS IS PERMITTED
 - STRAP U POINTS 14 16 WHEN CONNECTION OF RING TONE IS REQUIRED ON CALLS EXTENDED TO LOCAL EXTENSIONS BY THE P.A.B.X. OPERATOR
 - STRAP U POINTS 89-91 WHEN IMMEDIATE BUSY FACILITY IS REQUIRED ON INCOMING CALLS FROM RING RETURN EARTH MAIN EXCHANGES STRAP U POINTS G1 G3 FOR RING RETURN BATTERY MAIN EXCHANGES
 - WHEN MISC CCT TO GBW 14721 IS USED OMIT CONNECTION SHOWN
 - ON SOME EARLIER EQUIPT BATT LEADS WERE 'BK' OR 'W'

NZ NOTE

A FOR INCOMING ONLY RELAY SETS STRAP SHELF JACK POINTS U15 U16 REMOVE WIRES FROM U17 & U19 JOIN ALL 3 WIRES TOGETHER & INSULATE

FIG. 1A
RELAY SET

SUPERSEDES GBW 13220

RETRACED	(6844)	4.8	89/76	FJ/M
NZ NOTE A AMENDED	(6125)	4.8	89/76	SFE
AMENDMENT PARTICULARS				
DATE				
BY				
CHKD				
APPD				
CHECKED				
BY				
DATE				
BY				
DATE				

20, 35 & 49 LINE P.A.B.X. EXCHANGE LINE CIRCUIT

SIZE 1 1/2" x 1 1/2" 50V W

44690

NZPO

GBW