

STATIONS EQUIPPED WITH AMPLIFIERS

1. GENERAL

1.01 This section covers telephone sets and amplifiers which are used to provide increased volume for customers with impaired hearing.

1.02 This feature may be provided by:

(a) Externally mounted amplifier key working in conjunction with a hand telephone or combined telephone set. Refer to Section C54.115, Key Equipment 10A and 6030A Key.

(b) Combined telephone sets having the amplifier as an integral part of set. Refer to Section C32.508, Telephone Sets, 332- and 334-type (Amplifier Sets) and Section C32.557, Telephone Sets, 532- and 533-type (Amplifier Sets). In certain cases, where the transmission of sound through the bone will be required, refer to Section C32.651, Bone Conduction Receiver.

2. USE

2.01 Table A shows impaired hearing equipment associated with various classes of service.

TABLE A

Manual and Dial Common Battery, LBT-CBS and Magneto								
Class of Service	Common Battery	Common Battery	Loc. Bat. Talk. Combat Signal	Magneto Station	Common Battery Telephone Sets Types			
	10A Key	6030A Key			332	334	532	533
Bridged Station, Flat and Message Rate	X	X	X	X	X	*	X	
Ring Party, Flat and Message Rate	X	X	X		X	*	X	
Tip Party of Flat Rate	X	X	X		X	*	X	
**Tip Party of 2-party Dial Message Rate		X				X	X	
**Tip Party of 2-party Flat Rate Automatic Ticketing (Note)		X				X	X	
**Tip Party of 2-party Flat Rate, Automatic Message Accounting, and Zone Registration		X				X	X	
4-party Selective 8-party Semiselective		X						X
PBX Stations 750 and 755 PBX Keyless, Divided Code Ringing	X	X	X		X	*	X	
Nonselective Party Stations			X	X	X	*	X	

Note: Step-by-step automatic message accounting.

*The 334-type telephone may be converted to 332-type telephone, see C32.508, Telephone Sets, 332- and 334-type (Amplifier Sets).

**Except flat rate services, as indicated.