

CENTRAL OFFICE BATTERY POLARITY FOR DIAL-TONE-FIRST (DTF) SERVICE

- 1.01** Coin present test for initial deposit:
- -48 volt battery on the tip side with ring side open.
- 1.02** Coin present test for 5 cent overtime or stuck coin test.
- +48 volt battery on the tip side with the ring side open.
- 1.03** In 1C/2C sets, totalizer homing for deposits of initial rate or more:
- ± 48 volt battery on the ring side of line to ground on the tip side.
- 1.04** In 1C/2C sets, totalizer homing for a deposit less than initial rate or after coin control has been applied:
- +48 volt battery on the ring side of the line to ground on the tip.
- 1.05** The application of coin control battery (± 130 volts) on tip with ring open.
- This is to prevent false operation of the station "A" relay.
- 1.06** Talking battery on all operator trunks; +48 volts on ring with ground on tip:
- This is required to read out coin tones less than initial rate.