

**COIN TRUNKS ASSOCIATED WITH
TELONE* M-911A COIN FREE ADAPTER
OPERATION TEST
STEP-BY-STEP OFFICE**

1. GENERAL

1.01 This section describes a method of testing Dial Tone First (DTF) coin box trunks (SD-31592 and SD-32539) associated with the *TELONE M-911A Coin Free Adapter*.

1.02 (Reserved for future use.)

2. APPARATUS

2.01 Portable coin telephone.

3. PREPARATION

STEP	ACTION	VERIFICATION
1	At distributing frame — connect portable coin phone to any nonworking line in coin group to be tested.	
2	Have coins (5, 10, 25 cents) available.	

4. METHOD

STEP	ACTION	VERIFICATION
3	Operate switchhook on coin phone as required to select the particular line finder, trunk and adapter.	
4	Take receiver off hook and deposit 25 cents.	No coin return.

* *Registered trademark of TELONE Corporation*

NOTICE
Not for use or disclosure outside the
Bell System except under written agreement

SECTION 227-625-904PT

STEP	ACTION	VERIFICATION
5	Depress switchhook.	Coin returns.
6	With receiver off hook deposit 5 cents, dial local number.	Dial tone breaks, recording is heard.
7	Depress switchhook.	Coin returned.
		<i>Note:</i> Coin may have returned when connected to recording.
8	With receiver off hook deposit 10 cents, dial local number.	Ringing is heard.
9	Place receiver on hook.	Coin returned.
10	With receiver off hook deposit 10 cents, dial local number that can be answered.	
11	Called number answers.	
12	Hang receivers up on both lines.	Coin is collected.
13	Dial operator and make a coin tone check. Have operator return each coin after check.	Coin tones heard. Each coin returned as requested.
14	Deposit one coin and have operator apply collect battery.	Coin is collected.
15	Request operator to call back (ring test) after coin phone is on hook.	Phone rings.
16	Answer operator's ring-back.	Ringing is silenced.
17	With operator on line, deposit coin and hang up.	Coin is collected automatically.
18	With receiver off hook deposit 10 cents and dial operator.	Operator answers and coin is returned.
	Non-Charge Service Code Test	
19	Dial a 3-digit noncharge service code (611, 411 etc.).	Operator answers.

STEP	ACTION	VERIFICATION
	Forced Disconnect Test (SD32539-01, Option ZF)	
20	Deposit 10 cents, dial local number.	Ringing is heard.
21	Called number answers, then disconnects.	Approximately 12 seconds after disconnect, the <i>called number</i> should go off hook and receive dial tone.
22	Tests completed. Disconnect coin phone from line equipment.	All circuits under test should be normal.