



**Fig. 1**

3.02 The diagram in Fig. 1 shows the line and ringer connections for bridged ringing lines. Line and ringer connections for bridged and grounded ringing lines of the classes of service for which the set is used are given in Table 1.

**Table 1**

Connections	Ringer Leads		Mtg. Cord		
	BK	R	R	GN	Y
*Bridged	C2	3	L1	L2	G
Ring Party	C2	L2	L2	L1	G
Tip Party	L2	C2	L1	L2	G

\*On bridged ringing lines strap terminal L<sub>2</sub> to terminal G. On grounded ringing lines, omit this strap. Local ground should not be connected through to yellow mounting cord conductor on bridged ringing lines.