

TABLE B
558C AND D LINE AND RINGER CONNECTIONS
(INTERNAL CONNECTIONS)

FEATURES (SIGNALING INCLUDED WITH ALL FEATURES)									CONNECTIONS TO TERMINALS INSIDE SET										
NUMBER OF LINES PICKED UP	RINGER IN SET USED AS		TURN KEY USED TO CUT OFF				EXCLUSION KEY USED TO CUT OFF		TURN KEY LEADS		EXCLUSION KEY LEADS (NOTE 6)					RINGER LEADS (NOTES 7, 8, AND 9)			
	LINE RINGER	COM OR PVT LINE RINGER	EXT STA OR EXT LINE RINGER	EXTERNAL COM OR PVT LINE RINGER	RINGER IN SET	AUXILIARY RECEIVER	EXT STA OR EXT LINE RINGER	RINGER IN SET			S - R	[S-G] (G-BK)	[R-Y] (Y)	[G-Y] (BK)	BL	W	R	BK	S
1	•		•				•		L2	L1	L2	L1	5	6	L2	L1	K	A	
1	•				•		•		L2	L1	L2	L1	5	6	3	4	K	A	
1	•		•		•		•		L2	L1	L2	L1	5	6	1	2	K	A	
1		•	•				•		L2	L1	L2	L1	5	6	E1	E2	A	A	
1		•			•		•		E1	E2	L2	L1	5	6	3	4	A	A	
1		•		•	•		•		E1	E2	L2	L1	5	6	1	2	A	A	
1	•					•	•		G	R	L2	L1	5	6	L2	L1	K	A	
2	•						•		L2	L1	1	2	5	6	1	2	K	A	
2		•					•		L2	L1	1	2	5	6	E1	E2	A	A	
2		•						•	L2	L1	E1	E2	5	6	5	6	A	A	