



NOTES:

1. INSIDE WIRE CONDUCTOR SHALL BE CONNECTED TO THE GROUND TERMINAL AT THE PROTECTOR OR EQUIVALENT ONLY IF REQUIRED FOR THE SERVICE BEING INSTALLED.
2. DISCONNECT (S) LEAD FROM B TERMINAL WHEN H5AA CORD IS USED AND TIP IDENTIFYING GROUND IS NOT PROVIDED, INSULATE AND STORE.
3. SET WIRED FOR BRIDGED RINGING.
4. INSIDE WIRING CABLE MAY BE USED IN PLACE OF "D" STATION WIRE.
5. H4DB OR H4DU HANDSET CORD SHALL BE USED FOR INDIV. OR BRIDGED RINGING, RING PARTY, AND TIP PARTY WITHOUT IDENT. GRD.
6. LAMP AND RESISTOR ARE PART OF H5AD HANDSET CORD REQUIRED FOR MESSAGE WAITING FEATURE ON AC1P BASE ONLY. IF 220AM OR 2220BM HAND TELEPHONE SET IS PROVIDED, THE 227-TYPE ADAPTER MUST BE REMOVED.

7. WHEN H4DU CORD IS PROVIDED A 227D AND 231B ADAPTER IS REQUIRED FOR AC1P BUT ONLY 227D ADAPTER IS REQUIRED FOR AC2P.
8. INSULATED AND STORED ON EARLY VERSION AC1P ONLY.
9. (W) LEAD PROVIDED IN AC1P BASE ONLY.
10. 220AM, 2220BM, AND 2220BMG ARE EQUIPPED FOR H4DU HANDSET CORD.

* INSULATED AND STORED.

AC1P or AC2P Telephone Base, Connections With 220A (MD), 220AM, 2220B (MD), 2220BM, or 2220BMG Hand Telephone Set