



TABLE 1

SERVICE	COLOR OF RINGER LEAD		COLOR OF MOUNTING CORD CONDUCTORS					
	BLK	R	R	GN	YEL	BLK	BL	
INDIVIDUAL LINE								
332 TYPE TEL SETS COME WIRED FOR THIS SERVICE AS SHOWN. SEE Δ								
TWO PARTY SELECTIVE OR PARTY TIP (NON-SELECT. PARTY)	GN	K	L ²	L ¹	GN	BLK	BL	
	K	GN	LI	L ²	GN	BLK	BL	

Δ FOR OTHER SERVICES, THESE CONNECTIONS INDICATE CHANGES THAT MUST BE MADE IN THE SET AS FURNISHED.

TABLE 2

VOLUME	CONTACTS			
	D	E	F	G
LOW	CLOSED	CLOSED	OPEN	OPEN
MEDIUM	CLOSED	OPEN	CLOSED	OPEN
HIGH	OPEN	OPEN	CLOSED	CLOSED

NOTES

- 332AW TEL SET EQUIPPED WITH APP. BLANK
- 332CW TEL SET EQUIPPED WITH DIAL
- SETS AS FURNISHED ARE WIRED WITH AMPLIFIER SELECTION (NORMALLY ON).
- THE BLACK AND BLUE LEADS OF THE MOUNTING CORD SHALL BE CONNECTED TO THE 4 1/2 VOLT BATTERY.