



NOTE:

LAMP AND RESISTOR ARE PART OF H5AD CORD ONLY FOR MESSAGE WAITING FEATURE. [Y] LEAD IS NOT TERMINATED IN SET PLUG.

* CHANGE TO 53A LAMP IF COMBINED LENGTH OF HAND TELEPHONE SET CORD AND (ADI BASE) MOUNTING CORD EXCEEDS 15 FEET.

() COLOR CODE H4DB CORD.

[] COLOR CODE H5AA OR H5AD CORD.

220A Hand Telephone Set—Wiring Diagram